

# ***Instructions for OES-ISC85X***

Please note that for all these instructions, numbers can only be inputted, cleared or edited while the display is flashing. If the display has no fields flashing, nothing can be entered. An image of the gameclock can be found at the end of these instructions.

## **Set Time**

1. Press *Game Time*.
2. Input the minutes and press *Enter*, or just press *Enter* if the fields are already correct.
3. Input the seconds and press *Enter*, or just press *Enter* if the fields are already correct.
4. Input the milliseconds and press *Enter*, or just press *Enter* if the fields are already correct.

**NOTE:** To start the time, flip the switch up. To stop the time, flip the switch down.

## **Set Period**

The periods will increase each time you press game time, but they can be changed manually if needed. To change the period manually:

1. Press *Period*.
2. Input the correct period number.
3. Press *Enter*.

## **Set Score**

1. Press *Home Score* or *Visitor Score*.
2. Enter the correct number.
3. Press *Enter*.

## **Set Penalty**

1. Press *Home Penalty* or *Visitor Penalty* until you get to an open penalty option.
2. Enter player number and press *Enter*.
3. Enter the minutes of the penalty that needs to be served (i.e. 2, 4 or 5). Press *Enter*.
4. Press *Enter* to accept the penalty seconds as :00.

**NOTE:** To add a second penalty (or higher), you will need to press *Home Penalty* or *Visitor Penalty* until the flashing fields are on an empty penalty option.

## **Clear Penalty**

1. Press *Home Penalty* or *Visitor Penalty* until you get to the correct penalty.
2. Press *Clear* then press *Clear* a second time until all the fields are blank.

## **Edit Penalty**

1. Press *Home Penalty* or *Visitor Penalty* until you get to the correct penalty.
2. If the player number is correct, press *Enter*. If it is wrong, input the correct number then press *Enter*.
3. If the penalty time is correct, press *Enter*. If it is wrong, correct the minutes and press *Enter*, then correct the seconds and press *Enter*.

## *Instructions for OES-ISC85X*

